

User interface and Functionality

The Casambi Cloud Gateway affords much of the same end-user functionality as the Casambi App, the latter being the user interface for this gateway.

Lighting control options

- Dim or turn on/off singular or groups of luminaires.
- Dim or turn on/off a whole network.
- Turn on/off scenes and animations.
- Control color temperature, hue and saturation utilizing the control slider in the app.
- Create and edit timers.

Security

- Instructions for the required network settings are provided in the installation guide.
- The Casambi Cloud Gateway initiates all network traffic – there are no incoming network connections.
- All internet connections are encrypted (HTTPS).
- We advise installers to follow industry best practices such as adding the gateway to a network that is separate from business-critical devices and storing the gateway in a secure location.

Further considerations

- For indoor use only.
- Use one Casambi Cloud Gateway per Casambi network.
- Works with Casambi's Evolution firmware.
- For remote control and monitoring of a Casambi network in real-time.
- Remote commissioning, configuration and updating of new nodes are not possible via the gateway.

Technical specification

The Casambi Cloud Gateway comes with Ethernet and Wi-Fi connections for internet access and flash memory on a hardware-dedicated SD card. It is based on the Raspberry Pi 4, which has 47 certifications spanning CE, FCC, IC, UK CA, KCC, and features the following specifications:

- Broadcom BCM2711, Quad-core Cortex-A72 (ARM v8) 64-bit SoC @ 1.5GHz
- 4GB LPDDR4-3200 SDRAM
- 2.4 GHz and 5.0 GHz IEEE 802.11ac wireless, Bluetooth 5.0, BLE
- Gigabit Ethernet
- USB-C and Ethernet ports
- 5V DC via USB-C connector (minimum 3A)
- Power over Ethernet (PoE) enabled
- Operating temperature: 32 – 122 degrees F ambient (0 – 50 degrees C ambient).