

## Installation Instructions – PM252

SL42 Multi-LIGHTZ

### Classification: IC-F / IC-4

Recessed luminaire where approved fixed building insulation material that can be safely be continuously exposed to 90°C is allowed to abut and cover the luminaire.

### Constant current:

500mA (max)

### Approved insulation:

Pink Batts, Bradford Gold, InsulPro Polyester insulation, Ecofleece, Autex Greenstuf, Earthwool, Premier insulation.

Contact Switch Lighting for other insulation information.

### Caution:

Always turn power off when connecting or disconnecting luminaires.

### Warranty:

**Luminaire:** 5 years

Proof of purchase is required.

Warranty will be void if the product is immersed fully in water.

See website for full warranty conditions.

### How many constant current lights per driver?

Click on the QR code to check max & min number of lights to connect:

or visit

[www.switch-lighting.co.nz/](http://www.switch-lighting.co.nz/)  
Library / Tips and Tricks




### Required clearance: Standard

Required clearance from structural members and building elements:

**SCB** = 0mm **HCB** = 0mm

### Cut-out



SL42 32mm

### Installation:

(by registered electrician only)

1. Ensure driver is disconnected from mains supply before connecting LED/s.
2. Connect the LED/s and driver in **SERIES**.
3. Ensure connections are watertight – LED/s and driver may be permanently damaged if not wired correctly.

